

## DorWatcher

The DorWatcher alarm is designed to prevent doors from being left open for extended periods. Typically installed on kitchen doors in student accommodation, where it activates if the door remains open for more than one minute. The alarm prompts those nearby to close the door, helping to prevent cooking smoke from drifting into corridors and triggering unwanted fire alarm activations. Once the door is closed, the alarm resets automatically.

### Normal Operation

1. When the protected door is opened an LED will flash every few seconds for visual testing.
2. If the door remains open Time Delay TD1, factory default set at 40 secs will elapse before a short warning chime is made.
3. If the door remains open Time Delay TD2, factory default set at 20 secs will then elapse.
4. If the door remains open after TD1 and TD2 have elapsed the unit will sound its main alarm tone.
5. Once in full alarm, the tone continues for 2 minutes, then continues every 30 seconds alerting people in the vicinity that the door is still open. To clear the alarm simply close the door.
6. If the door is closed at any point the unit will reset. The next time the door is opened the timers will restart.

### Time Delay – TD1 and TD2 times are adjustable as follows:

TD1 (secs)	TD2 (secs)	Total Time to Alarm
20	10	30 seconds
40	20	1 minute (Factory Default)
160	20	3 minutes
400	20	7 minutes

**Simple Inspection** - DorWatcher's installed in locations prone to tampering / vandalism are fitted with anti-tamper screws and cages. Inspection for signs of tampering should be completed on a regular basis.

**Simple Visual check** - Open the protected door, if the LED on the front panel flashes within 10 seconds the system is working correctly, if the LED does not flash and the alarm does not activate after the preset time delays, contact your installation company for advice.

**Battery fault indication** - The battery powered DorWatcher DW304 has a built in battery fault monitor. If the unit beeps as soon as the door is opened, this indicates that the batteries are running low and should be changed.

DW304	Battery powered
DW305	12 vdc powered
DW306	Mains powered

### Benefits and Features

- Robust ABS plastic enclosure
- A box tamper switch activates tamper tone if the frontcover is removed
- Clear instructions displayed on the unit
- Models available - battery, 12vdc or 240vac mains
- Surface mounting door contact provided with 1m of cable pre connected
- Cable clips and fixing screws provided
- Audible battery fault monitor
- Simple installation
- Manufactured in the UK



### Dimensions (mm)



### Optional Cage and Anti-tamper screws

**CG100** - Cage designed to protect our range of products from vandalism and misuse.

**FIX/16** - 4off / pack used to secure CG100

**FIX/16/ATS** - Anti tamper screwdriver bit suits FIX/16 screws  
**FIX/17** - Pack of 5 anti tamper screws for DorWatcher lid and door contact

**FIX/17/ATS** - Anti tamper screwdriver bit suits FIX/17 screws